

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices per IEC 62353, IEC 60601 and VDE 0701-0702

3-447-031-03  
1/7.19

- Preconfigured test sequences for quickly testing operating equipment
- One universal, adjustable test sequence
- One test sequence executed with individual measurements
- Suitable for use by trained persons
- Extensive data management and storage concept for test results and individual measurements (up to 50,000 data records) – allocation of measurements/tests to devices and customers
- Quick access to measuring and test functions via the double rotary switch, direct selection keys and softkeys
- High-resolution, brilliant 4.3" TFT color display
- Unique multiple measurement permits convenient recording of several measuring points
- Automatic DUT connection and protection category detection
- Compact, impact resistant housing with integrated rubber protector
- Comprehensive, legally secure preparation of test reports
- Interfaces for data entry (two USB A) and data transmission (one USB B)
- Extensive setting options for international use (language, keyboard, character set, date, time)
- Testing of various PRCD types such as PRCD-S/PRCD-K (also with protective conductor resistance measurement for variants with switched PE) with integrated "VDE 0701-0702-PRCD" test sequence



- **R<sub>PE</sub> test** with 200 mA or 10 A test current (optional: 25 A)
- **Applied parts:** 10 configurable connections (4 mm sockets)
- Connections for 2<sup>nd</sup> test probe and voltage measurement
- **Test sequences per IEC 62353** and IEC 60601 (option KA01), and measurements via APP sockets
- **Single fault conditions** – adjustable, with and without mains and applied part
- **Test conditions** – adjustable, data entry via **touchscreen**
- **Database functions** permit the creation of a complete test structure with customer or device views

### Including SECUTEST DB+ database expansions

- **Remote control** possible from PC (IZYTRONIQ)
- **Additional database elements:** property, building, floor and room – in order to better be able to structure comprehensive data – plus additional department and cost center fields
- Multi-print – **print-out of several/all test reports** (to a connected Z721S thermal printer) which are available for a device under test by pressing just one key
- Create user-defined **report templates** and manage them in the **SECULIFE ST PRO** – including company logo
- **Export** of all data (master data and measured values) as file to USB flash drive
- **Import** of all test object master data (no measured values) from **IZYTRONIQ** or from a USB flash drive to the **SECULIFE ST PRO**
- Create **user-defined test sequences** in **IZYTRONIQ** and upload them to the **SECULIFE ST PRO**

### Including SECUTEST DB COMFORT database expansions

- New **"medical" database object** – device with extended entry options
- Searches started with the **"Search All" softkey** now search the new "UDI" field (unique device identification) at medical devices as well.
- **User-defined test sequences** – the number of user-defined sequences has been increased to 24.
- **Move** test objects – "moving" of (medical) devices within the tree can be initiated by pressing and holding the respective element in the tree display.
- **Touch-edit** – "editing" of a (medical) device can be started by pressing and holding the respective element of the detail display in the main window.
- **Auto-store** – the auto-store function can be activated in the setup menu so that the results of automatic testing are saved immediately under the selected test object.
- **Push-print** – a PC connected to the test instrument can cause the **SECULIFE ST PRO** to enter an operating mode in which data are transmitted directly to the connected PC instead of being stored at the tester.
- **Quick edit** – the quick edit option can be activated when entering a new test object so that all other fields can be filled out immediately after entering the ID number.
- New **test interval** database field (also for synchronization with **IZYTRONIQ**)

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Overview, Test Instrument's Scope of Functions

Switch Position	Measuring Functions Test Current/Voltage	Measurement Type Connection Type
<b>Single measurements, rotary switch level: green</b>		
<b>RPE</b>	$R_{PE}$ <b>Protective conductor resistance</b>	PE(TS) - P1 passive PE(TS) - P1 (TS to) PE(mains) - P1 <sup>6</sup> PE(mains) - P1 clamp <sup>2,6</sup> P1-P2 <sup>3</sup>
	$I_P$ Test current 200 mA Test current 10 A <sup>1</sup> (feature G01) Test current 25 A <sup>1</sup> (feature G02)	
<b>RINS</b>	$R_{ISO}$ <b>Insulation resistance (PC I/PC II)</b>	LN(TS) - PE(TS) LN(TS) - P1 P1-P2 <sup>3</sup> PE(mains) - P1 PE(TS) - P1 LN(TS) - P1//PE(TS) LN(TS) - APP PE(mains) - APP PE(TS) - APP P1//PE(TS) - APP P2 - APP
	$U_{INS}$ Test voltage	
<b>IPE</b>	$I_{PE\approx}$ <b>Protective conductor current, TRMS</b>	Direct
	$I_{PE-}$ AC component	Differential
	$I_{PE=}$ DC component	Alternative
	$U_{LPE}$ Test voltage	AT3-Adapter <sup>2</sup> Clamp <sup>2</sup>
	$U_{Gen}$ Reference voltage (alternative)	
<b>IT</b>	$I_{T\approx}$ <b>Touch current, TRMS</b>	Direct P1
	$I_{T-}$ AC component	Differential P1
	$I_{T=}$ DC component	Alternative P1
	$U_{LPE}$ Test voltage	Perm. conn. P1
	$U_{Gen}$ Reference voltage (alternative)	Alternative P1-P2
<b>IE</b>	$I_{E\approx}$ <b>Device leakage current, RMS</b>	Direct
	$I_{E-}$ AC component	Differential
	$I_{E=}$ DC component	Alternative
	$U_{LPE}$ Test voltage	AT3-Adapter <sup>2</sup> Clamp <sup>2</sup>
	$U_{Gen}$ Reference voltage (alternative)	
<b>IA</b>	$I_{A\approx}$ <b>Leakage current from the applied part RMS</b>	Direct P1 Direct APP Alternative P1 Alternative APP Perm. conn. P1 Perm. con. APP APP - P2 <sup>7</sup>
	$U_{LPE}$ Test voltage	
	$U_{Gen}$ Voltage at applied part	
<b>IP</b>	$I_{P\approx}$ <b>Patient leakage current, RMS</b>	Direct P1
	$I_{P-}$ AC component	Direct APP
	$I_{P=}$ DC component	Perm. conn. P1
	$U_{LPE}$ Test voltage	Permanent connection APP
<b>IPA</b>	$I_{PA\approx}$ <b>Patient leakage current, TRMS</b>	Direct APP
	$I_{PA-}$ AC component	Permanent connection APP
	$I_{PA=}$ DC component	
	$U_{LPE}$ Test voltage	
<b>U</b>	$U_{\approx}$ <b>Probe voltage, RMS</b>	PE-P1 PE-P1 (PD to *) * Polarity parameter
	$U_{-}$ AC component	
	$U_{=}$ DC component	
	$U_{\approx}$ <b>Measuring voltage, RMS<sup>2</sup></b>	V - COM V - COM (PD to)
<b>P</b>	<b>Function test at the test socket</b>	
	<b>I</b> Current between L and N	
	<b>U</b> Voltage between L and N	
	<b>f</b> Frequency	Polarity parameter
	<b>P</b> Active power	
	<b>S</b> Apparent power	
<b>PF</b> Power factor		

Switch Position	Measuring Functions Test Current/Voltage	Measurement Type Connection Type
<b>Probe measuring functions</b>		
<b>EL1</b>	Extension cord test with adapter: continuity, short-circuit, polarity (wire reversal <sup>5</sup> )	EL1 adapter AT3-III-E adapter VL2E adapter
<b>EXTRA</b>	Reserved for expansion during the course of software updates	
	$t_A$ <sup>4</sup> PRCD time to trip for 30 mA PRCDs	
	$^{\circ}C$ Temperature measurement <sup>2</sup> with Pt100/Pt1000	V - COM
	$I_Z$ Current clamp measurement <sup>2</sup> with current clamp sensor	V - COM

<sup>1</sup> 10/25 A- $R_{PE}$  measurements are only possible with line voltages of 115/230 V and line frequencies of 50/60 Hz.

<sup>2</sup> Voltage measuring inputs

<sup>3</sup> Connection of a 2<sup>nd</sup> test probe for 2-pole measurement

<sup>4</sup> Measurement of time to trip is not possible in IT systems.

<sup>5</sup> No checking for reversed polarity takes place when the EL1 adapter is used.

<sup>6</sup> Type of connection not available with feature G02

### Key

Alternative = alternative measurement (equivalent leakage current measurement)

Differential = differential current measurement

Direct = direct measurement

APP = applied part

LN(TS) = short-circuited L and N conductors at test socket

P1 = measurement with test probe P1

P1-P2 = 2-pole measurement with test probes P1 and P2

PE-P1 = measurement between PE and test probe P1

PE(TS) = protective conductor at the test socket

PE(mains) = protective conductor at the mains connection

Switch Position	Standard	Measurement type, connection type (* feature KA01)
<b>Automated test sequences, rotary switch level: orange</b>		
<b>Preconfigured (freely adjustable) test sequences – default settings</b>		
<b>A1</b>	<b>IEC 62353</b>	Passive, test socket, 1 group of BF APPs A-K, PCI
<b>A2</b>	<b>IEC 62353</b>	Passive, test socket, 1 group of BF APPs A-K, PCII
<b>A3</b>	<b>IEC 62353</b>	Passive, test socket, 1 group of BF APPs A-K, PCI + II
<b>A4</b>	<b>IEC 62353</b>	Active, automatic detection, 1 group of BF APPs A-K, PCI
<b>A5</b>	<b>IEC 62353</b>	Active, automatic detection, 1 of group of BF APPs A-K, PCII
<b>A6</b>	<b>IEC 62353</b>	Active, automatic detection, 1 group of BF APPs A-K, PCI + II
<b>A7 *</b>	<b>IEC 60601 3. A.</b>	Active, automatic detection, 1 group BF APPs A-K, PCI
<b>A8 *</b>	<b>IEC 60601 3. A.</b>	Active, automatic detection, 1 of group of BF APPs A-K, PCII
<b>A9 *</b>	<b>IEC 60601 3<sup>rd</sup> edition</b>	Active, automatic detection, 1 group BF APPs A-E, PCI + II Active, automatic detection, 1 group CF APPs F-K, PCI + II

### Antimicrobial Properties

The instrument has been equipped with antimicrobial properties. This is intended to impede the growth of germs, counteract microbial colonization and destroy microorganisms.

### Display with Selectable Language

The display panel consists of a backlit, color multi-display at which menus, setting options, measurement results, instructions and error messages, as well schematic and wiring diagrams appear.

The display and user prompting can be set to the desired language depending on the country in which the test instrument is used.

### Data Entry

Data can be entered, for example, via a barcode reader, an RFID scanner or a USB keyboard connected to the USB port, or via the softkey keyboard when it appears at the display. The touchscreen

## Test Instrument for Measuring the Electrical Safety of Medical Devices

permits convenient entry of data and comments, and menu-driven operation is still possible via the softkeys.

### Creating a Database

A complete test structure with data regarding customer buildings, floors, rooms and test objects can be created in the test instrument. This structure makes it possible to assign single measurements or test sequences to devices under test belonging to various customers. Manual single measurements can be grouped together into a so-called "manual sequence".

In the case of the test instrument with database expansion, a test structure can be created at the PC with the help of **IZYTRONIQ** software and subsequently transferred to the test instrument.

### Data Interfaces

Structures set up in, and measurement data saved to the test instrument can be imported to **IZYTRONIQ** report generating software via the USB slave port. Data can then be archived at the PC, comments can be added with the software and reports can be generated.

The following input and output devices can be connected to the two integrated USB master ports:

- External keyboard as well as barcode or RFID reader
- USB flash drive for data backup, import, export and reports
- Printer

### Software Updates

The test instrument can always be kept current thanks to firmware which can be updated via the USB slave port.

### Report Generating Functions

All of the values required for approval reports or device logbooks for electrical devices (e.g. per ZVEH) can be measured with this test instrument. All measured data can be documented and archived thanks to the measurement and test report that can be printed with a thermal printer which has been connected to the USB port, or stored to a PC.

### Automatic Detection of Measuring Point Changes

During protective conductor measurement, the test instrument recognizes whether or not the test probe is in contact with the protective conductor, which is indicated by means of two different acoustic signals. This function is very useful where several protective conductor connections need to be tested.

## Mains Connection Analysis

Line voltage and frequency are measured and compared with the data specified in Setup. Momentary voltage or nominal voltage in accordance with the standard is required, for instance in order to calculate measured values for the leakage current measurement.

### Automatic Detection of Mains Connection Errors

The device automatically recognizes mains connection errors if the conditions in the following table have been fulfilled. The user is informed of the type of error, and all measuring functions are disabled in the event of danger.

Type of Mains Connection Error	Message	Condition	Measurements
Voltage at protective conductor PE to finger contact (START/STOP key)	Display at the instrument	Press START/STOP key $U > 25 \text{ V}$ key $\rightarrow$ PE; $< 1 \text{ M}\Omega^2$	All measurements disabled

Type of Mains Connection Error	Message	Condition	Measurements
Protective conductor PE and phase conductor L reversed and/or neutral conductor N interrupted		Voltage at PE $> 100 \text{ V}$	Not possible (no supply power)
Line voltage $< 180 \text{ V} / < 90 \text{ V}$ (depending on mains)		$U_{L-N} < 180 \text{ V}$ $U_{L-N} < 90 \text{ V}$	Conditionally possible <sup>1</sup>
Test for IT/TN system	Display at the instrument	Connection $N \rightarrow PE > 20 \text{ k}\Omega$	Possible under certain circumstances

<sup>1</sup> 10 A/25 A- $R_{PE}$  measurements are only possible with line voltages of 115/230 V and line frequencies of 50/60 Hz.

<sup>2</sup> If the user of the test instrument is too well insulated, the following error message may appear: "Interference voltage to PE"

## Analysis of Connection and Condition of the DUT

Depending on the measurement or how the DUT is connected, the following conditions are checked and displayed before measurement.

Test Function	Condition
Short-circuit test L–N	Short-circuit / DUT starting current
	No short-circuit (AC test)
	$R \leq 2.5 \Omega^2$
	$R > 2.5 \Omega^2$
Open-circuit voltage $U_0$ 4.3 V, short-circuit current $I_k < 250 \text{ mA}$	
Short-circuit test LN–PE	Short-circuit
	No short-circuit (AC test)
	$R \leq 2 \text{ k}\Omega$
	$R > 2 \text{ k}\Omega$
Open-circuit voltage $U_0$ 230 V AC, short-circuit current $I_k < 1.5 \text{ mA}$	
On test	On (DUT passive)
	Off (DUT active)
	$R < 250 \text{ k}\Omega$
	$R > 300 \text{ k}\Omega$
Open-circuit voltage $U_0$ 230 V AC, short-circuit current $I_k < 1.5 \text{ mA}$	
Special test	No probe
	Probe detected
	$R > 2 \text{ M}\Omega$
	$R < 500 \text{ k}\Omega$
Protection category detection (only with country-specific version <sup>1</sup> )	
	Protective conductor found: PC I
	No protective conductor: PC II
	$R < 1 \Omega$
	$R > 10 \Omega$
Safety shutdown <sup>1</sup>	
Triggered at following residual current value (selectable)	$> 10 \text{ mA} / > 30 \text{ mA}$
Triggered at following probe current value During leakage current measurement	
During protective conductor resistance measurement	$> 250 \text{ mA}$
Connection test (only with country-specific version <sup>1</sup> )	
Checks whether the DUT is connected to the test socket.	
	DUT power cable found
	No DUT power cable
	$R < 1 \Omega$
	$R > 10 \Omega$
Insulation test	DUT set up in a well-insulated fashion
	DUT set up in a poorly insulated fashion
	$R \geq 500 \text{ k}\Omega$
	$R < 500 \text{ k}\Omega$
$PE_{\text{Mains}} - PE_{\text{Socket}}$ : Open-circuit voltage $U_0$ 50 V DC, $I_k < 2 \text{ mA}$	
Overcurrent protection	
Shutdown in the event of a continuous flow of current via the test socket:	$I > 16.5 \text{ A}$
Our SECUTEST BASE10/PRO, SECULIFE ST BASE(25) and SECULIFE ST PRO test instruments permit active testing of devices with nominal current (load current) of up to 16 A. The test socket on the respective test instrument is equipped with 16 A fuses to this end and the switching capacity of the internal relays is also 16 A. Starting current of up to 30 A is permissible. In the case of test objects for which a starting current of greater than 30 A can be expected, we urgently recommend the use of a test adapter for larger starting currents, for example test adapters from the AT3 series.	

<sup>1</sup> Applies to M7050 with feature B00, B09

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Applications

Regulations and standards in accordance with which the test instrument is manufactured and tested:

DIN EN 61010-1 VDE 0411-1	Safety requirements for electrical equipment for measurement, control and laboratory use – general requirements
DIN EN 62353 DIN VDE 0751-1	Medical electrical equipment – Recurrent test and test after repair of medical electrical equipment
DIN EN 60529/ VDE 0470-1	Test instruments and test procedures Degrees of protection provided by enclosures (IP code)
DIN EN 61326-1 VDE 0843-20-1	Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 1: General requirements
DIN EN 61326-2-2 VDE 0843-20-2-2	Part 2-2: Particular requirements – Test configurations, operational conditions and performance criteria for portable test, measuring and monitoring equipment used in low-voltage distribution systems
IEC 61557-16 DIN EN 61557-16 VDE 0413-16	Electrical safety in low voltage distribution systems up to 1000 V AC and 1500 V DC – Equipment for testing, measuring or monitoring of protective measures – Part 16: Devices for testing the effectiveness of protective measures of electrical devices and/or electrical medical devices

### Scope of Delivery

#### Standard Version (country-specific)

- 1 Test instrument
- 1 Mains power cable
- 1 Test probe, 2 m, not coiled
- 1 USB cable, USB A to USB B, 1.0 m long
- 1 Plug-on alligator clip
- 1 KS17-ONE cable set for voltage measuring inputs
- 1 Calibration certificate
- 1 Set of condensed operating instructions
- 1 Set of comprehensive operating instructions on the Internet for download from [www.gossenmetrawatt.com](http://www.gossenmetrawatt.com)
- 1 Card with registration key for **IZYTRONIQ BUSINESS Starter** software



IZYTRONIQ is newly developed test software with which the entire testing scenario can be visualized, managed and documented in an audit-proof, instrument-independent fashion. And thus for the first time ever, measurement and test data from various test instruments and multimeters can be combined into a single test and documented. Intuitive operation and a modern look assure quick access to all functions.


The software is available on different scales and in different versions for the commercial trades, for industry and for training applications.

### Backlit Multi-Display Samples


#### Single Test – Initial Screen with Parameters Display




#### Help – Schematic and Wiring Diagram




#### Test Function for Test Step in the Test Sequence



#### Results of a Test Sequence per IEC 62353



#### Database Structure – List of Test Results



## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Characteristic Values

Function	Measured Quantity	Display Range / Nominal Range of Use	Resolution	Nominal Voltage $U_N$	Open-Circuit Voltage $U_0$	Nominal Current $I_N$	Short-Circuit Current $I_K$	Internal Resistance $R_I$	Reference Resistance $R_{REF}$	Measuring Uncertainty	Intrinsic Error	Overload Capacity	
												Value	Time
Tests, 62638 (DIN VDE 0701-0702) / IEC 62353 (VDE 0751)	Protective conductor resistance <sup>12</sup> <b>RPE</b>	1 ... 999 m $\Omega$	1 m $\Omega$	—	< 24 V AC or DC	—	> 200 mA AC / DC	—	—	$\pm(15\% \text{ rdg.} + 10 \text{ d})$ > 10 d > 10.0 $\Omega$ : $\pm(10\% \text{ rdg.} + 10 \text{ d})$	$\pm(10\% \text{ rdg.} + 10 \text{ d})$ > 10 d	264 V 250 mA	Cont.
		1.00 ... 9.99 $\Omega$	10 m $\Omega$									16 A AC <sup>5</sup>	
		10.0 ... 27.0 $\Omega$	100 m $\Omega$									$\geq 42 \text{ A AC}$ 11	
	Insulation resistance <sup>9</sup> <b>Riso</b>	10 ... 999 k $\Omega$	1 k $\Omega$	50 ... 500 V DC	1.0 • $U_N$ ... 1.5 • $U_N$	> 1 mA	< 2 mA	—	—	$\pm(5\% \text{ rdg.} + 4 \text{ d})$ > 10 d $\geq 20 \text{ M}\Omega$ : $\pm(10\% \text{ rdg.} + 8 \text{ d})$	$\pm(2.5\% \text{ rdg.} + 2 \text{ d})$ > 10 d $\geq 20 \text{ M}\Omega$ : $\pm(5\% \text{ rdg.} + 4 \text{ d})$	264 V	Cont.
		1.00 ... 9.99 M $\Omega$	10 k $\Omega$										
		10.0 ... 99.9 M $\Omega$	100 k $\Omega$										
		100 ... 300 M $\Omega$	1 M $\Omega$										
	Leakage current, alternative measurement <sup>2</sup> <b>IPE, IT, IE, IA</b>	0 ... 99 $\mu\text{A}$	1 $\mu\text{A}$	—	50 ... 250 V~ -20/+10%	—	< 1.5 mA	> 150 k $\Omega$	1 k $\Omega$ $\pm 10 \Omega$	$\pm(5\% \text{ rdg.} + 4 \text{ d}) > 10 \text{ d}$ > 15 mA: $\pm(10\% \text{ rdg.} + 8 \text{ d})$	$\pm(2\% \text{ rdg.} + 2 \text{ d}) > 10 \text{ d}$ > 15 mA: $\pm(5\% \text{ rdg.} + 4 \text{ d})$	264 V	Cont.
		100 ... 999 $\mu\text{A}$	1 $\mu\text{A}$										
		1.00 ... 9.99 mA	10 $\mu\text{A}$										
		10.0 ... 30.0 mA	100 $\mu\text{A}$										
	Leakage current, direct measurement <sup>3</sup> <b>IPE, IT, IE, IA, IP, IPA</b>	only IP, IPA: 0.0 ... 99.9 $\mu\text{A}$	100 nA	—	—	—	—	1 k $\Omega$ $\pm 10 \Omega$	1 k $\Omega$	$\pm(5\% \text{ rdg.} + 10 \text{ d})$ > 10 d	$\pm(2.5\% \text{ rdg.} + 5 \text{ d})$ > 10 d	264 V	Cont.
		0 ... 99 $\mu\text{A}$	1 $\mu\text{A}$										
		100 ... 999 $\mu\text{A}$	1 $\mu\text{A}$										
		1.00 ... 9.99 mA	10 $\mu\text{A}$										
	Leakage current, differential current measurement <sup>4</sup> <b>IPE, IT, IE</b>	0 ... 99 $\mu\text{A}$	1 $\mu\text{A}$	—	—	—	—	—	—	$\pm(5\% \text{ rdg.} + 10 \text{ d}) > 10 \text{ d}$ $\pm(5\% \text{ rdg.} + 4 \text{ d})$	$\pm(2.5\% \text{ rdg.} + 2 \text{ d})$ > 10 d	264 V	Cont.
100 ... 999 $\mu\text{A}$		1 $\mu\text{A}$											
1.00 ... 9.99 mA		10 $\mu\text{A}$											
10.0 ... 30.0 mA		100 $\mu\text{A}$											
Function test at test socket	Line voltage $U_{L-N}$ <sup>10</sup>	100.0 ... 240.0 V~	0.1 V	—	—	—	—	—	—	—	$\pm(2\% \text{ rdg.} + 2 \text{ d})$	264 V	Cont.
	Load current $I_L$	0 ... 16.00 A <sub>RMS</sub>	10 mA	—	—	—	—	—	—	—	$\pm(2\% \text{ rdg.} + 2 \text{ d})$	16 A	Cont.
	Active power P	0 ... 3700 W	1 W	—	—	—	—	—	—	—	$\pm(5\% \text{ rdg.} + 10 \text{ d})$ > 20 d	264 V 20 A	Cont. 10 min.
	Apparent power S	0 ... 4000 VA	1 VA	Calculated value, $U_{L-N} \cdot I_V$							$\pm(5\% \text{ rdg.} + 10 \text{ d})$ > 20 d	264 V	Cont.
	Power factor PF with sinusoidal waveform: $\cos\phi$	0.00 ... 1.00	0.01	Calculated value, P / S, display > 10 W							$\pm(10\% \text{ rdg.} + 5 \text{ d})$	264 V	Cont.
	Line frequency f	0 ... 420.0 Hz	0.1 Hz	—	—	—	—	—	—	—	$\pm(2\% \text{ rdg.} + 2 \text{ d})$	264 V	Cont.
$t_A$ PRCD	Time to Trip	0.1 ... 999 ms	0.1 ms	—	—	30 mA	—	—	—	$\pm 5 \text{ ms}$	—	264 V	Cont.
Voltage measurement	Probe voltage (probe P1 to PE) $\overline{\text{---}}$ , $\sim$ and $\overline{\text{---}}$	0.0 ... 99.9 V 100 ... 264 V	100 mV 1 V	—	—	—	—	3 M $\Omega$ 1 M $\Omega$	—	—	$\pm(2\% \text{ rdg.} + 2 \text{ d})$ $\pm(2\% \text{ rdg.} + 5 \text{ d})$ $\pm(5\% \text{ rdg.} + 5 \text{ d})$ > 10 kHz ... 20 kHz	264 V 300 V $\overline{\text{---}}$ , $\sim$ and $\overline{\text{---}}$	Cont.
	Measuring voltage (V-COM sockets $\overline{\text{---}}$ , $\sim$ and $\overline{\text{---}}$ )	0.0 ... 99.9 V 100 ... 300 V											
$I_{\text{Leakage}}$	Leakage current via AT3-IIIIE adapter Z745S <sup>8</sup>	0.00 ... 0.99 mA~	0.01 mA	—	—	—	—	—	—	—	$\pm(2\% \text{ rdg.} + 2 \text{ d})$ > 10 d without adapter	253 V	Cont.
		1.0 ... 9.9 mA~	0.1 mA										
		10 ... 20 mA~	1 mA										
Temp	Temperature with Pt100 sensor	-200.0 ... +850.0 °C	0.1 °C	—	< 20 V~	—	1.1 mA	—	—	—	$\pm(2\% \text{ rdg.} + 1 \text{ }^\circ\text{C})$	10 V	Cont.
	Temperature with Pt1000 sensor	-150.0 ... +850.0 °C											

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

Function	Measured Quantity	Display Range / Nominal Range of Use	Resolution	Nominal Voltage $U_N$	Open-Circuit Voltage $U_0$	Nominal Current $I_N$	Short-Circuit Current $I_K$	Internal Resistance $R_I$	Reference Resistance $R_{REF}$	Measuring Uncertainty	Intrinsic Error	Overload Capacity	
												Value	Time
I <sub>Clamp</sub>	Current via current clamp sensor [1 mV : 1 mA] (V-COM sockets <sup>6,7</sup> )	1 ... 99 mA ~	1 mA (1 mV)	—	—	—	—	—	—	—	±(2% rdg.+2 d) > 10 d 20 Hz ... 20 kHz without clamp	253 V	Cont.
		0.1 ... 0.99 A ~	0.01 A (10 mV)										
		1.0 ... 9.9 A ~	0.1 A (100 mV)										
		10 ... 300 A ~	1 A (1 V)										
	Current via current clamp sensor [10 mV : 1 mA] (V-COM sockets <sup>6,7</sup> )	0.1 ... 9.9 mA ~	0.1 mA (1 mV)	—	—	—	—	—	—	—			
		10 ... 99 mA ~	1 mA (10 mV)										
		0.10 ... 0.99 A ~	0.01 A (100 mV)										
		1.0 ... 30.0 A ~	0.1 A (1 V)										
	Current via current clamp sensor [100 mV : 1 mA] (V-COM sockets <sup>6,7</sup> )	0.01 ... 0.99 mA ~	0.01 mA (1 mV)	—	—	—	—	—	—	—			
		1.0 ... 9.9 mA ~	0.1 mA (10 mV)										
		10 ... 99 mA ~	1 mA (100 mV)										
		0.10 ... 3.00 A ~	0.01 A (1 V)										
	Current via current clamp sensor [1000 mV : 1 mA] (V-COM sockets <sup>6,7</sup> )	1 ... 99 µA ~	1 µA (1 mV)	—	—	—	—	—	—	—			
		0.10 ... 0.99 mA ~	0.01 mA (10 mV)										
		1.0 ... 9.9 mA ~	0.1 mA (100 mV)										
		10 ... 300 mA ~	1 mA (1 V)										

<sup>2</sup> Known as equivalent leakage current or equivalent patient leakage current from previous standards

<sup>3</sup> Protective conductor current, touch current, device leakage current, patient leakage current

<sup>4</sup> Protective conductor current, touch current, device leakage current

<sup>5</sup> Only with feature G01

<sup>6</sup> Only with feature I01

<sup>7</sup> Measurement types IPE\_clamp and IG\_clamp

<sup>8</sup> Measurement types IPE\_AT3 adapter and IG\_AT3 adapter

<sup>9</sup> The upper range limit depends on the selected test voltage.

<sup>10</sup> Voltage at the test socket may be lower than measured line voltage due to components which limit inrush current.

<sup>11</sup> Only with feature G02

<sup>12</sup> Specifications for measurement type PE(mains) – P1 after offset balancing

### Reference Ranges

Line voltage 230 V AC ±0.2%

Line frequency 50 Hz ±2 Hz

Waveform

Sine (deviation between RMS and rectified value < 0.5%)

Ambient temperature +23 °C ±2 K

Relative humidity 40 ... 60%

Load resistance Linear

### Nominal Ranges of Use

Nominal line voltage 100 V ... 240 V AC

Nominal line frequency 50 Hz ... 400 Hz

Line voltage

waveform Sinusoidal

Temperature 0 °C ... + 40 °C

### Ambient Conditions

Storage temperature - 20 °C ... + 60 °C

Relative humidity Max. 75%, no condensation allowed

Elevation Max. 2000 m

Place of use Indoors, except within specified ambient conditions

**Key:** rdg. = reading (measured value), d = digit(s)

### Test Times, Automated Sequence

Test times ("measurement duration" parameter) can be set separately for each rotary switch position during configuration of the sequence parameters. Test times are neither tested nor calibrated.

### Emergency Shutdown During Leakage Current Measurement


As of 10 mA of differential current (can also be set to 30 mA), automatic shutdown ensues within 500 ms. This shutdown does not take place during leakage current measurement with clamp meter or adapter.

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Influencing Quantities and Influence Error

Short form designation	Influencing Quantity	RPE	RINS	IPE, IT, IE, IA Leakage Current, Alternative Measurement	IPE, IT, IE, IA, IP, IPA Leakage Current, Direct Measurement	IPE, IT, IE Leakage Current, Differential Current Measurement
A	Intrinsic Uncertainty	$\pm(10\% \text{ rdg.} + 10 \text{ d}) > 10 \text{ d}$	$\pm(2.5\% \text{ rdg.} + 2 \text{ d}) > 10 \text{ d}$	$\pm(2\% \text{ rdg.} + 2 \text{ d}) > 10 \text{ d}$	$\pm(2.5\% \text{ rdg.} + 2 \text{ d}) > 10 \text{ d}$	$\pm(2.5\% \text{ rdg.} + 2 \text{ d}) > 10 \text{ d}$
			$\geq 20 \text{ M}\Omega$ : $\pm(5\% \text{ rdg.} + 4 \text{ d})$	$> 15 \text{ mA}$ : $\pm(5\% \text{ rdg.} + 4 \text{ d})$		
E1	Reference position $\pm 90^\circ$	0%	0%	0%	0%	0%
E2	Supply voltage	2.5%	2.5%	2.5%	2.5%	2.5%
E3	Temperature 0 °C ... +40 °C	2.5%	2.5%	2.5%	2.5%	2.5%
E9	Mains harmonics				1%	1%
E11	Low frequency magnetic fields	2.5%	2.5%	2.5%	2.5%	2.5%
I12	Load current [A]					2.5%

Frequency response in accordance with the figure to the right is taken into consideration for all leakage current measurements (IPE, IT, IE, IA, IP, IPA) (direct, differential, alternative).



### Power Supply

Supply network	TN, TT or IT
Line voltage	100 ... 240 V AC
Line frequency	50 ... 400 Hz
Power consumption	200 mA test: approx. 32 VA 10 A test: approx. 105 VA 25 A test: approx. 280 VA
Mains to test socket (e.g. for function test)	Continuous max. 3600 VA, power is conducted through the instrument only, switching capacity: $\leq 16 \text{ A}$ , ohmic load, the AT3-IIS32 adapter (Z745X), for example, can be used for current $> 16 \text{ A AC}$

### USB Data Port

Type	USB slave for PC connection
Type	2 ea. USB master for data input devices * with HID boot interface for USB flash drive for data backup, for USB flash drive for saving reports as BMP files, for printer *

\* See following page for compatible devices

In the remote operating mode, the test instrument can be controlled via the USB slave data interface.

### Bluetooth® data interface 2.1 + EDR (feature M01)

### Electrical Safety

Protection category	I per IEC 61010-1/EN 61010-1/VDE 0411-1
Nominal voltage	230 V
Test voltage	2.3 kV AC 50 Hz or 3.3 kV DC (mains circuit / test socket to mains PE terminal, USB, finger contact, probe(s), APP sockets, test socket)
Measuring category	250 V CAT II
Pollution degree	2
Safety shutdown	At DUT differential current of $> 10 \text{ mA}$ , shutdown time: $< 500 \text{ ms}$ , can also be set to $> 30 \text{ mA}$ with following probe current during: – Leakage current measurement: $> 10 \text{ mA} \sim / < 500 \text{ ms}$ – Protective conductor resistance measurement: $> 250 \text{ mA} \sim / < 1 \text{ ms}$ with continuous flow of current $I > 16.5 \text{ A}$
Fuse links	Mains fuses: 2 ea. FF 500V/16A Probe fuse: M 250V/250mA <b>Feature G01:</b> 10 A RPE test current: 1 ea. FF 500V/16A <b>Feature J01:</b> Applied parts: 2 ea. M 250V/250mA

### Electromagnetic Compatibility

Product standard	DIN EN 61326-1:2013 DIN EN 61326 -2-2: 2013
------------------	--

Interference Emission		Class
EN 55011		B
IEC 61000-3-2		B
IEC 61000-3-3		B
Interference Immunity	Test Value *	Evaluation Criterion
EN 61000-4-2	Contact/atmos. – 4 kV/8 kV	B
EN 61000-4-3	10 V/m (80 MHz ... 1 GHz)	A
EN 61000-4-4	Mains connection – 2 kV	B
EN 61000-4-5	Mains connection – 1 kV (LN), 2 kV (LPE)	B
EN 61000-4-6	Mains connection – 3 V	A
EN 61000-4-8	30 A/m	A
EN 61000-4-11	0%: 1 period 0%: 250/300 periods 40%: 10/12 periods 70%: 25/30 periods	B C C C

### Mechanical Design

Display	4.3" color display (9.7 x 5.5 cm) backlight, 480 x 272 pixels at 24-bit color depth (true color)
Touchscreen	Touch controlled user interface
Dimensions	W x H x D: 295 x 145 x 150 mm Height with handle: 170 mm
Weight	Feature G00/G01: approx. 2.5 kg Feature G02: approx. 4 kg
Protection	Housing: IP 40 Test socket: IP 20 Applied parts: IP 20 per DIN VDE 0470, part 1 / EN 60529 Housing with antimicrobial properties per JIS standard Z 2801:2000

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Accessories (not included)

#### Z751A Barcode Reader

For connection to the USB master port at the test instrument, and for reading in barcodes. This makes it possible to conveniently insert the ID numbers of DUTs into single measurements and test sequences.

This device is based on the concept of an instinctive scanning distance and provides best possible reading performance. Green Spot technology provides "good-read" projection directly on the code. The device is equipped with a USB port



#### Z721E Barcode Printer

For connection to the USB master port at the test instrument, and for printing out test reports.

**Encoding:** Code39, Code128, EAN13, Text, QR Code \*, Micro QR Code, DataMatrix, Aztec

\* QR Code is a registered trademark of DENSO WAVE INCORPORATED



#### Z721S Thermal Printer


For connection to the USB master port at the test instrument, and for printing out test reports.



#### SCANBASE RFID (Z751E) (RFID read/write)

Compact reading and writing device with a USB port for programming and reading 13.56 MHz transponders in accordance with ISO15693.

RFID tags can also be written directly from the test instrument with the program.



#### CEE Adapter for Testing Single and 3-Phase Electrical Devices (Z745A)

The Z745A CEE adapter allows for quick and efficient testing of devices equipped with a CEE plug. The adapter is equipped with the following CEE flush-type socket outlets: 5-pole 16 A, 5-pole 32 A and 3-pole 16 A. Furthermore, the adapter includes five 4 mm safety sockets to which 3-phase devices without permanently attached plug or conventional measurement cables can be connected, e.g. by means of quick clamp terminals (not included). The following tests can be performed on devices with CEE plugs with the help of the CEE adapter:

- Testing of protective conductor continuity
- Insulation resistance, alternative leakage current (equivalent leakage current)
- Function test (3-pole CEE outlet only)

The Z745A CEE adapter may also be used as an adapter for connecting devices with 3-pole CEE plugs to common earthing contact outlets.

#### VL2 E (Z745W)

Test adapter with single and 3-phase plug connectors up to CEE 32A



#### AT16-DI 3-Phase 16 A Differential Current Adapter (Z750A)

Devices which are equipped with a 5-pole, 16 A / 6 h CEE plug can be quickly and efficiently tested with the AT16-DI CEE adapter.

The following tests can be performed on devices with CEE plugs with the help of the AT16-DI CEE adapter:

- Testing of protective conductor continuity
- Insulation resistance, alternative leakage current (equivalent leakage current)
- Measurement of protective conductor resistance with the following methods: equivalent leakage current / differential current / direct
- Function test

This differential current adapter is also available in a variant with a 5-pole 32 A / 6 h CEE plug with the designation AT32-DI CEE adapter.





## Test Instrument for Measuring the Electrical Safety of Medical Devices

### SECU-cal 10 Calibration Adapter (Z715A)

The calibration adapter is used for testing the measuring uncertainty of test instruments in accordance with DIN VDE 0701-0702 / IEC 62353 (VDE 0751). As a rule, these instruments must be tested once each year as set forth by DGUV Regulation 3 (accident prevention regulation, previously BGV A3), as well as for certification in accordance with the ISO 9000 quality standard.



All limit values for the required tests per DIN VDE, as well as protective conductor resistance, insulation resistance, equivalent leakage current, differential and/or touch as well as housing leakage current, must be tested.

### EL1 Adapter for Testing Single-Phase Extension Cables (Z723A)



### AT3-III-E Three-Phase Adapter (Z745S)

Test adapter for active and passive testing of single and 3-phase electric devices, as well as extension cords, in combination with SECUTEST.../SECULIFE test instruments.

Operation is simple and safe. The test adapter is connected to a 3-phase 16 A mains outlet, and to the respective test instrument. Testing is performed without reversing polarity at the device under test, either automatically or manually, and is controlled by the test sequence of the utilized test instrument. Safety shutdown occurs if the preset residual current value is exceeded.



# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### SORTIMO L-BOXX (Z503D)

Plastic system case, outside dimensions:  
W x H x D  
450 x 255 x 355 mm

Z701D foam insert for test instrument and accessories must be ordered separately, see below.



### Foam Insert for SORTIMO L-BOXX (Z701D)



### F2010 Universal Carrying Pouch (Z700G)



Outside dimensions:  
W x H x D  
380 x 230 x 270 mm  
(without carrying strap)

### F2000 Universal Carrying Pouch (Z700D)



Outside dimensions:  
W x H x D  
380 x 310 x 200 mm  
(without buckles, handle and carrying strap)

### F2020 Universal Carrying Pouch (Z700F)



Outside dimensions:  
W x H x D  
430 x 310 x 300 mm  
(without buckles, handle and carrying strap)

Sample Content

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### List of Order Features

Device Variants			SECULIFE ST PRO (M7050 AA13 E01 G01 H01 I01 J01 KB01 KD01 M00)
	<b>Article Number, Basic Instrument</b>		<b>M7050</b>
		<b>Article Number / Feature</b>	<b>AA13</b>
<b>Connections – Country-Specific Mains Plug and Test Socket</b>			
	Germany with detection of connection and protection category	<b>B00</b>	–
	UK	<b>B01</b>	–
	FR/CZ/PL	<b>B03</b>	–
	China	<b>B04</b>	–
	USA	<b>B05</b>	–
	Off	<b>B06</b>	–
	DK	<b>B07</b>	–
	IT	<b>B08</b>	–
	CH with detection of connection and protection category	<b>B09</b>	–
<b>User interface language (can be subsequently changed to any of the other languages listed below)</b>			
	German	<b>C00</b>	–
	English	<b>C01</b>	–
	French	<b>C02</b>	–
	Italian	<b>C03</b>	–
	Spanish	<b>C04</b>	–
	Czech	<b>C05</b>	–
	Dutch	<b>C06</b>	–
	Polish	<b>C07</b>	–
<b>Data entry via touchscreen</b>			
	None	<b>E00</b>	
	Included	<b>E01</b>	✓
<b>R-PE test current for protective conductor measurement</b>			
	200 mA	<b>G00</b>	
	200 mA and 10 A <sup>1</sup> (not in combination with G02)	<b>G01</b>	✓
	200 mA and 25 A	<b>G02</b>	
<b>Connection of a 2<sup>nd</sup> test probe</b>			
	None	<b>H00</b>	
	Included	<b>H01</b>	✓
<b>DVM function (digital voltmeter) with 2 additional measurement inputs, COM–V</b>			
	None	<b>I00</b>	
	Included	<b>I01</b>	✓
<b>Connection for applied parts</b>			
	None	<b>J00</b>	
	Included	<b>J01</b>	✓
<b>Additional test sequences</b>			
	None	<b>KA00</b>	✓
	IEC 60601	<b>KA01</b>	
<b>Database expansion</b>			
	None	<b>KB00</b>	
	Included (corresponds to Z853R – SECUTEST DB+)	<b>KB01</b>	✓
<b>Database Comfort</b>			
	None	<b>KD00</b>	
	Included (corresponds to Z853S – SECUTEST DB COM-FORT)	<b>KD01</b>	✓
<b>Bluetooth</b>			
	None	<b>M00</b>	✓
	Included	<b>M01</b>	
<b>DAkkS calibration certificate (language combinations)</b>			
	In D/GB/F	<b>P00</b>	
	In D/GB/PL	<b>P01</b>	
	In D/GB/IT	<b>P02</b>	
<b>DAkkS calibration certificate (recalibration)</b>			
		<b>Key:</b> ✓ preset	

Sample order SECULIFE ST PRO with English user interface:

**M7050 AA13 C01 E01** (Highlighted features the table – in this case in boldface with gray background in – belong to the fixed basic equipment of the SECULIFE ST PRO, and other features can be selected as desired.)

AA13: device variant SECULIFE ST PRO, C01: user interface, keyboard layout and test sequences in English, G01: R-PE test current for protective conductor measurement: 200 mA and 10 A

<sup>1</sup> 10 A/25 A-R<sub>PE</sub> measurements are only possible with line voltages of 115/230 V and line frequencies of 50/60 Hz.

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

### Order Information for Accessories

Designation	Type	Article No.
<b>Mains cable</b>		
Cable set for connecting test instruments to the mains without using an earthing contact outlet, and for connecting DUTs. Consists of coupling socket with 3 permanently connected cables, 3 measurement cables, 3 plug-on pick-off clips and 2 plug-on test probes	KS13	GTY3624065P01
<b>Adapter for testing 3-phase current consumers</b>		
Adapter for connecting DUTs: 3-pole 16 A, 5-pole 16 A + 32 A, 5 ea. 4 mm socket – For all tests without mains voltage for single and 3-phase electrical devices – For leakage current measurement per direct or differential current method	CEE adapter	Z745A
3-phase 16 A/32 A adapter (test case) – For all tests without mains voltage for single and 3-phase electrical devices – For tests at single and 3-phase extension cords – For leakage current measurements with direct method – For leakage current measurements with differential current method	AT3-III-E <sup>D</sup>	Z745S
Test adapter for testing devices with CEE16 and CEE32 connectors (max. 20 A load capacity)	AT3-IIS <sup>D</sup>	Z745T
Same as AT3-IIS but with 32 A load capacity	AT3-II S32 <sup>D</sup>	Z745X
3-phase 16 A differential current adapter	AT16-DI	Z750A
3-phase 32 A differential current adapter	AT32-DI	Z750B
Test adapter with single and 3-phase plug connectors up to CEE 32A – For all tests without mains voltage for single and 3-phase electrical devices – For tests at single and 3-phase extension cords	VL2E	Z745W
Adapter cable, red CEE 5-pole 16 A plug to red CEE 5-pole 32 A coupling, 0.5 m, 5 x 1.5 sq. mm	CEE16/CEE32 adapter cable	Z750F
<b>Adapter for testing single-phase extension cords</b>		
Adapter for testing single-phase extension cords including earth contact and inlet plug inserts	EL1	Z723A
Plug insert for using the EL1 adapter in Switzerland	PRO-CH	GTZ3225000R0001
<b>Calibration adapter</b>		
Calibration adapter for test instruments per DIN VDE 0701-0702/IEC 62353 (VDE 0751) (max. 200 mA) <b>cannot be used for 10 A protective conductor test current</b>	SECU-cal 10	Z715A
<b>Probe cables</b>		
Probe cable with test probe and 2 m probe cable (not coiled), 300 V CAT II 16 A	PC2	Z745D
Probe cable with test probe and 2 m probe cable (coiled), 300 V CAT III 16 A	SK2W	Z745N
5 m probe cable for protective conductor measurement, 300 V CAT II 16 A	PC5	Z745O
Brush probe	Z745G	Z745G
Distributor for connecting five 4 mm and five 2 mm test probes for measuring multiple, accessible housing parts or applied parts	SV5	Z745J

Designation	Type	Article No.
Cable set (1 pair of measurement cables) 1.2 m, with VDE-GS mark, 600 V CAT IV 1 A <sup>1</sup> , 1000 V CAT III 1 A <sup>1</sup> 1000 V CAT II 16 A <sup>2</sup> <sup>1</sup> With plugged-on safety caps <sup>2</sup> Without plugged-on safety caps	KS17-2	GTY3620034P0002
2 pieces in a plastic bag, diameter: 4 mm, length: 1.0 m, 1000 V CAT III, 19 A, blue	Measuring cable set, blue	Z746A
2 pieces in a plastic bag, diameter: 4 mm, length: 1.0 m, 1000 V CAT III, 19 A, black/red	Measuring cable set, black/red	Z746B
<b>Current clamp sensors</b>		
Leakage current clamp meter (current clamp sensor) for <b>SECUTEST PRO</b> and <b>SECULIFE ST PRO</b> 0.1 mA ... 25 mA AC, frequency range: 50 Hz ... 1 MHz, transformation ratio: 100 mV/mA, clamp opening: max. 40 mm cable dia.	SECUTEST CLIP	Z745H
Switchable current clamp sensor, 1 mA ... 15 A and 1 A ... 150 A, frequency range: 45...65 ... 500 Hz, transformation ratio: 1 mV/mA and 1 mV/A, clamp opening: max. 15 mm cable dia.	WZ12C <sup>D</sup>	Z219C
Leakage current clamp meter, 0.1 mA ... 25 mA, 100 mV/mA	SECUTEST CLIP <sup>D</sup>	Z745H
<b>Temperature sensors</b>		
Pt100 temperature sensor, -40 ... +500 °C for surface and immersion measurements	Z3409	GTZ3409000R0001
Pt1000 temperature sensor, class B for measurement in gases and liquids, -50 ... +220 °C	TF220	Z102A
Pt100 oven sensor, -50 ... +550 °C	TF550	GTZ3408000R0001
Dip-stick oil temperature sensor, Pt1000, class B, -50 to +500 °C, sensor: 3 mm dia. x 810 mm long	TF400CAR	Z102C
<b>Pouches and cases</b>		
Carrying pouch for <b>SECULIFE ST PRO</b>	F2000 <sup>D</sup>	Z700D
Large carrying pouch for test instrument sets	F2020	Z700F
Universal carrying pouch with flexible compartments and display protection for <b>SECULIFE ST PRO</b>	F2010	Z700G
Plastic system case	SORTIMO L-BOXX	Z503D
Foam insert for SORTIMO L-BOXX with compartment for <b>SECULIFE ST PRO</b>	Foam SORTIMO L-BOXX Secutest4	Z701D
Foam insert for SORTIMO L-BOXX GM with compartment for adapter	Foam SORTIMO L-BOXX adapter	Z701E

## Test Instrument for Measuring the Electrical Safety of Medical Devices

Designation	Type	Article No.
<b>Report generating accessories</b>		
<b>RFID system</b>		
RFID read/write for USB port (frequency: 13.56 MHz)	SCANBASE RFID	Z751E
RFID tags per ISO 15693, dia. approx. 22 mm, self-adhesive, 500 pcs.	Z751R	Z751R
RFID tag per ISO 15693, dia. approx. 30 mm, 2 mm thick with 3 mm hole, 500 pcs.	Z751S	Z751S
RFID tag per ISO 15693, pigeon ring, dia. approx. 7.5 mm, 250 pcs.	Z751T	Z751T
<b>Barcode scanners</b>		
Barcode scanner for USB connection	Z751A	Z751A
<b>Barcode printer</b>		
Barcode and label printer including soft- ware, with USB port for PC or test instru- ment Encoding: Code39, Code128, EAN13, Text, QR Code, Micro QR Code, DataMatrix, Aztec	Z721E	Z721E
Label set for Z721D barcode and label printer (qty. x width: 3 x 24 / 1 x 18 / 1 x 9 mm, 8 m long)	Z722D	Z722D
Label set for Z721D barcode and label printer (qty. x width: 5 x 18 mm, 8 m long)	Z722E	Z722E
<b>Thermal printer</b>		
Thermal printer for printing test reports, including user's manual on CD-ROM, lithium battery, power pack and mains cable, USB cable, 1 roll of thermal paper	Z721S	Z721S
Thermal paper for Z721S, 10 rolls of thermal paper, 12/50 mm dia., 30 m x 112 mm, outside coating	Z722S <sup>D</sup>	Z722S
See also separate data sheet for ID systems regarding RFID scanners, barcode readers and printers.		

<sup>D</sup> Data sheet available

For additional information regarding accessories please refer to:

- Measuring Instruments and Testers catalog
- [www.gossenmetrawatt.com](http://www.gossenmetrawatt.com)

# SECULIFE ST PRO

## Test Instrument for Measuring the Electrical Safety of Medical Devices

---

---

Edited in Germany • Subject to change without notice • PDF version available on the Internet

 **GOSSEN METRAWATT**

GMC-I Messtechnik GmbH  
Südwestpark 15  
90449 Nürnberg • Germany

Phone: +49 911 8602-111  
Fax: +49 911 8602-777  
e-mail [info@gossenmetrawatt.com](mailto:info@gossenmetrawatt.com)  
[www.gossenmetrawatt.com](http://www.gossenmetrawatt.com)