

1308/1309 are easy to use with pocket size and light weight, providing accurate display light level in terms of Foot Candles (FC) or LUX over wide range. Just turning the Function Switch to select the "lux" scale and setting the range to desired range, then removing the photo detector to light source in a horizontal position and reading the illuminance normal from the LCD display. When the measurement is completed, replace the photo detector from the light source.

- Over-range indication
- Long life silicon photo diode inside
- Measurement rate: 1.5 times per second

Widest range to 40,000Fc/
400,000 Lux



Model 1308

Features

	1308	1309
LCD display counts	4000	4000
Auto Ranging	*	*
Analog bargraph/segments	41-segments	41-segments
Peak Hold	*	*
Relative mode	*	*
Max and Data Hold	*	*
Auto Power Off	*	*
Low battery indication	*	*
User selectable FC/Lux	*	*
USB interface		*
Total accuracy: for C.I.E standard illuminate A(2856K)		

Specifications

Max. Range	50,000lux/Fc(1300,1301); 400,000Lux(1308)
Accuracy	$\pm 5\% \pm 10d (< 10,000\text{Lux})$
	$\pm 10\% \pm 10d (> 10,000\text{Lux})$
Max. Resolution	0.1Lux/0.01Fc
Measuring rate	1.5 times/second
Photo Detector	115mm x 60mm x 27mm

Accessories : One 9V battery and One Photo Detector (1308/1309)

Carrying case and Gift box.